

Командный лист для GPS tracker tk201 (new)

Функция	Команды	Пример
Инициализация	123456cmd,st=1	123456cmd,st=1
P.S' To cancel all the settings ,you need this commands ,but if you forget the password,you can send command " FORMAT" to recover factory settings		
Изменение пароля	pa=888999	123456cmd,pa=888999
P.S:the passwod should be 6 digitals		
Авторизация	em=131222222 (в примере указаны 5 разных номеров)	123456cmd,em=131222222/131333333/131444444/131555555/131666666
P.S: you can configure 5 authorized numbers at same time		
Отмена авторизации	нет команд для этого	no command for it
P.S: only can intialize device again		
Автотрекинг (в секундах)	ti=30	123456cmd,ti=30
P.S: interval report time is 30 seconds		
Отмена автотрекинга	no command for it	no command for it
P.S: only can intialize device again		
Однократный запрос	tk=1	123456cmd,tk=1
P.S: only get 1 time postion to server		
Geo-fence	no command for it	no command for it
P.S: only can configure the zone on server		
Превышение скорости	sp=60	123456cmd,sp=60
P.S: the speed is km/h,the value should be over 60		
Отмена оповещ. о скорости	sp=0	123456cmd,sp=0
P.S: Cancel speed alert		
Movement alert	mo=1	123456cmd,mo=1
P.S: The tracker will move 300m at least and wait 5min to get alert		
Cancel movement alert	mo=0	123456cmd,mo=0

P.S: Cancel movement alert		
Low Battery Alert	no needing to set up	no needing to set up
P.S:when the back up battery is less than 3.7v,it will send' lo+google map link" to authorized number.only alert time.you also can check the voltage from the data.		
IMEI Checking	no command for it	no command for it
P.S: If you want to know device IMEI,you can call it and get sms reply to check IMEI		
Time Zone setting	ZO=2	123456cmd,zo=2
P.S: Hungry GMT time is timezone123456 2 currently		
IP and Port Setting	ip=211.154.139.227:9001	123456cmd,ip=211.154.139.227:9001
P.S: for gprs working mode,you need to configure ip and port		
Cancel IP and Port setting	no command for it	no command for it
P.S: only can Initialize device		
APN Setting	ap=cmnet	123456cmd,ap=cmnet
P.S: please contact with your sim card operator to confirm apn		
APN user name setting	na=cmnet	123456cmd,na=cmnet
P.S:If the APN has username,this command is for it		
APN password setting	co=cmnet	123456cmd,co=cmnet
P.S:If the APN has password,this command is for it		
alert to sms and gprs at same time	in=1	123456cmd,in=1
P.S: 1----for this function on; 0-----stop this function		
turn off device via command	of=1	123456cmd,of=1
P.S:next time only can turn on device by hand		
restart device	rt=1	123456cmd,rt=1
P.S:restart device		
on/off button setting	sw=0/1	123456cmd,sw=1
P.S:0-----for turning on/ turning off device; 1-----only for turning on device; the default is sw=1		
version checkin	ver=?	ver=?
P.S: don't add password,just send command directly :ver=?		
flash firmware over the air	up=v140310.bin/ 121.37.40.240 /user/ idc200999/21	123456cmd,UP=file name/FTP server IP/user/password/port
P.S: flash the firmware over the air,can't support USB cable flash.		